

700.0 kVA VOLVO-PENTA GENERATOR

FEATURES & BENEFITS

- Maximum 770.0 kVA, 400 V, 1500 RPM
- Industrial brushless alternator with AVR
- Steel baseframe, retention basin & fuel tank with sensor
- 950 litre tank for 8 hrs @ 75% Load
- Test report, manuals and electrical drawings supplied
- Modular design, open and silent version available
- Industrial silencer and coupling flange
- Electrical panel mounted on board the unit with digital control device installed in metal box
- Compact for easy handling and use
- World wide after sales service and technical support



GENERAL DATA	
Model:	V700GXHD
Continuous power (PRP):	700.0 kVA
Continuous power (PRP):	560.0 kW
Stand-by power (LTP):	770.0 kVA
Stand-by power (LTP):	616.0 kW
Power factor:	0.8
Frequency (Hz):	50 Hz
Voltage (V):	400 V
Width:	1840 mm
Length:	4700 mm
Height:	2540 mm
Weight:	6740 kgs
Tank Capacity:	950 l
dBa @ 7m:	77.0 dBA

ALTERNATOR	
Alternator brand:	STAMFORD
Alternator model:	HCI6G
L.T.P. Power:	860.0 kVA
P.R.P. Power:	810.0 kVA
Connection:	Series star
Phases:	Three phases with neutral
Terminal Number:	12
IP Protection:	23
Alternate Alternator:	

ENGINE DATA	
Brand:	VOLVO-PENTA
Model:	TWD1645GE
Cylinders:	6
RPM:	1500
Cubic Capacity:	16.12
Air Intake:	Turbocharged
Standard Voltage:	24
SAE:	1-14
BMEP:	3100
Cooling:	Water
Flywheel P.R.P. Power:	595.0 kW
Flywheel Stand-by Power:	654.0 kW
Oil Qty:	48.0 l
Antifreeze Qty:	141.0 l
Heat from Radiator:	405.0 kW
Heat from Exhaust:	473.0 kW
Exhaust Temperature:	501 °C
Cooling Airflow:	684.00 m ³ /min
Combustion Airflow:	43.53 m ³ /min
Exhaust Airflow:	106.00 m ³ /min
TA Luft / TA Luft 2:	Not available / Not available
Stage:	Not available

FUEL CONSUMPTION	
Fuel Cons. at 110%:	152.1 l/h
Fuel Cons. at 100%:	138.4 l/h
Fuel Cons. at 75%:	106.5 l/h
Fuel Cons. at 50%:	74.6 l/h
Fuel Cons. at 25%:	39.5 l/h

- * Specs subject to change without prior notice.
- * Measurements based on ISO8528-1 Standards
- * Picture may vary from actual product.

Maputo, Moçambique

+258 85 176 3143

comercial@cobalt.co.mz

www.cobalt.co.mz