

## 50 KVA DIESEL GENERATOR

### FEATURES & BENEFITS

- Maximum 55 kVA, 380V, 1500 RPM
- Constant voltage AVR (Automatic Voltage Regulator)
- 24 Volt Electric Starter
- 75 Litre Fuel Tank, 10 Hours @ 75% load
- Silent Version ( $\pm 72$  dBA)
- Four cylinder, Turbo, water cooled Diesel Engine
- Three Phase Output
- DeepSea DSE6120 Digital Control Panel
- Low oil pressure system
- Low water cut out engine protection



PRODUCT COLOUR MAY VARY.

GENERAL DATA	
<b>Model:</b>	BPD50S3
<b>Prime Power (P.R.P):</b>	50 kVA
<b>Stand-by Power (L.T.P):</b>	55 kVA
<b>Amps:</b>	83 A
<b>Power Factor / COS:</b>	0.8
<b>Frequency:</b>	50 Hz
<b>Voltage:</b>	380 V
<b>Phases:</b>	Three Phase
<b>Engine Speed:</b>	1500 RPM
<b>Length:</b>	2280 mm
<b>Width:</b>	900 mm
<b>Height:</b>	1150 mm
<b>Weight:</b>	1073 kg's
<b>Tank Capacity:</b>	75 l

ADDITIONAL	
<b>Running Time:</b>	10 Hours @ 75% load
<b>Structure Type:</b>	Silent
<b>Noise Level (7m):</b>	72 dBA
<b>Auto Voltage Regulator:</b>	Constant voltage AVR
<b>ISO9001 Certified:</b>	Yes
<b>CE Certified:</b>	Yes
<b>Fuel Cons. @ 100% Load:</b>	9.4
<b>Fuel Cons. @ 75% Load:</b>	7.1
<b>Fuel Cons. @ 50% Load:</b>	4.7

ENGINE DATA	
<b>Brand:</b>	FAW
<b>Model:</b>	4DX22-65D-HMS20W
<b>Type:</b>	Four cylinder, Turbo, water cooled Diesel Engine
<b>Starting System:</b>	24 Volt Electric Starter
<b>Auto-Decompression:</b>	Yes
<b>Cubic Capacity (l):</b>	3.86
<b>Compression Ratio:</b>	17:1
<b>Rated Power (kW/RPM):</b>	48 / 1500
<b>Fuel Type:</b>	Diesel
<b>Lube Oil:</b>	15W40
<b>Low Pressure Alert:</b>	Yes
<b>Low Fuel Cut Out:</b>	Yes

CONTROL PANEL	
<b>Model:</b>	DeepSea DSE6120
<b>Type:</b>	Digital Control Panel
<b>Analogue Inputs:</b>	2
<b>Mains Phase Voltage:</b>	Yes
<b>Mains Line Voltage:</b>	Yes

ALTERNATOR	
<b>Model:</b>	DPC224D
<b>Pole Number:</b>	4
<b>Excitation Mode:</b>	Self Excitation

Maputo, Moçambique

+258 85 176 3143

comercial@cobalt.co.mz

www.cobalt.co.mz

## 4DX22-65D-HMS20W DIESEL ENGINE



ITEM	MEASURE	VALUE
Engine model		4DX22-65D-HMS20W
Type		4-cylinder 4-stroke
Air intake type		Turbocharged
Cooling mode		Water cooling
Governor mode		Electronic
Bore × Stroke	mm	102 × 118
Compression ratio		17:1
Rated speed	RPM	1500
Displacement	L	3.86
Rated power (without fan)	kW	48
Standby power (without fan)	kW	53
Emission compliant		Stage II
The flywheel shell interface		SAE3
		Flywheel for 11.5" flexible coupling
Dry weight of GenPac	kg	410
Overall Dimension	mm	1480 × 705 × 900
Fan consumption	kW	3.0
27°C air consumption	m <sup>3</sup> /min	3.9
Heat rejection of exhaust	kW	43.5
Exhaust gas temp. after turbine	°C	480
Exhaust gas flow	m <sup>3</sup> /min	10.4
Heat rejection from engine	kW	3.3
Heat rejection of coolant	kW	29
Charging Alternator		35A / 28V
Starter Motor		4.5kW / 24V

# DSE6110/20 MKII

## AUTO START & AUTO MAINS FAILURE CONTROL MODULES

**DSE6110 MKII**

**DSE6120 MKII**

**KEY FEATURES**

- Large back-lit text display
- Multiple display languages
- Heated display option available
- DSENet® expansion compatible
- Data logging facility
- Fully configurable via PC using USB communication
- Front panel configuration
- Efficient power save mode
- 3 phase generator sensing
- 3 phase mains (utility) sensing (DSE6120 MKII only)
- Generator/load power monitoring (kW, kV A, kV Ar, pf)
- Accumulated power monitoring (kW h, kVA h, kVAR h)
- Generator/load current monitoring and protection
- Generator overload protection (kW)
- Breaker control via fascia buttons
- Fuel and start outputs, configurable when using CAN
- 4 configurable DC outputs
- 4 configurable analogue/digital inputs
- Support for 0 to 10 V &

- 4 to 20 mA oil pressure sensors
- 6 configurable digital inputs
- Configurable staged loading outputs
- CAN, MPU and alternator speed sensing in one variant
- 3 engine maintenance alarms
- Engine speed protection
- Engine hours counter
- Engine pre-heat
- Engine run-time scheduler
- Engine idle control for starting & stopping
- Fuel pump control
- Real time clock
- Battery voltage monitoring
- Start on low battery voltage
- Configurable remote start input
- 1 alternative configuration
- Comprehensive warning, electrical trip or shutdown protection upon fault condition
- LCD and LED alarm indication
- Customisable information screens
- Configurable event log (100)
- Tier 4 ECO engine support including exhaust fluids & filters

- J1939-75 instrumentation output, configurable CAN instrumentation and alarms
- Start on low battery
- Enhanced alarm functionality
- Low load alarm

**KEY BENEFITS**

- Automatically transfers between mains (utility) and generator (DSE6120 MKII only)
- Increased input and output expansion capability via DSENet®
- User-friendly set-up and button layout for ease of use
- Multiple parameters are monitored simultaneously which are clearly displayed on a large back-lit text display via multiple languages
- The module can be configured to suit a wide range of applications
- Uses DSE Configuration Suite PC Software for simplified configuration
- Licence-free PC software
- IP65 rating (with optional gasket) offers increased resistance to water ingress

**SPECIFICATIONS**
**DC SUPPLY**

**CONTINUOUS VOLTAGE RATING**  
8 V to 35 V Continuous

**CRANKING DROPOUTS**

Able to survive 0 V for 50 mS, providing supply was at least 10 V before dropout and supply recovers to 5 V. This is achieved without the need for internal batteries. LEDs and backlight will not be maintained during cranking.

**MAXIMUM OPERATING CURRENT**

100 mA at 12 V, 105 mA at 24 V

**MAXIMUM STANDBY CURRENT**

60 mA at 12 V, 55 mA at 24 V

**MAXIMUM SLEEP CURRENT**

40 mA at 12 V, 35 mA at 24 V

**GENERATOR & MAINS (UTILITY)**

**VOLTAGE RANGE**  
15 V to 415 V AC (Ph to N)  
26 V to 719 V AC (Ph to Ph)

**FREQUENCY RANGE**

3.5 Hz to 75 Hz

**INPUTS**

**DIGITAL INPUTS A to F**  
Negative switching

**ANALOGUE INPUT A**

Configurable as:  
Negative switching digital input  
0 V to 10 V  
4 mA to 20 mA  
0 Ω to 240 Ω

**ANALOGUE INPUTS B TO D**

Configurable as:  
Negative switching digital input  
0 Ω to 480 Ω

**OUTPUTS**
**OUTPUT A (FUEL)**

10 A short term, 5 A continuous, at supply voltage

**OUTPUT B (START)**

10 A short term, 5 A continuous, at supply voltage

**AUXILIARY OUTPUTS C, D, E & F**

2 A DC at supply voltage

**DIMENSIONS**

**OVERALL**  
216 mm x 158 mm x 43 mm  
8.5" x 6.2" x 1.5"

**PANEL CUT-OUT**

184 mm x 137 mm  
7.2" x 5.3"

**MAXIMUM PANEL THICKNESS**

8 mm  
0.3"

**STORAGE TEMPERATURE RANGE**

-40 °C to +85 °C  
-40 °F to +185 °F

**OPERATING TEMPERATURE RANGE**

**NON HEATED DISPLAY VARIANT**  
-30 °C to +70 °C  
-22 °F to +158 °F

**HEATED DISPLAY VARIANT**

-40 °C to +70 °C  
-40 °F to +158 °F

**OPTIONAL PARTS**

PART	PART NUMBER
IP65 Gasket	020-521

**RELATED MATERIALS**
**TITLE**

DSE6110/20 MKII Installation Instructions  
DSE6110/20 MKII Operator Manual  
DSE6110/20 MKII Configuration Suite PC Manual

**PART NO.**

053-173  
057-226  
057-224

**DEEP SEA ELECTRONICS PLC UK**

Highfield House, Hunmanby Industrial Estate, Hunmanby YO14 0PH  
**TELEPHONE** +44 (0) 1723 890099 **FACSIMILE** +44 (0) 1723 893303  
**EMAIL** sales@deepseapl.com **WEBSITE** www.deepseapl.com

**DEEP SEA ELECTRONICS INC USA**

3230 Williams Avenue, Rockford, IL 61101-2668 USA  
**TELEPHONE** +1 (815) 316 8706 **FACSIMILE** +1 (815) 316 8708  
**EMAIL** sales@deepseausa.com **WEBSITE** www.deepseausa.com

# DSE6110/20 MKII

## AUTO START & AUTO MAINS FAILURE CONTROL MODULES

The DSE6110 MKII Auto Start Control Module and the DSE6120 MKII Auto Mains (Utility) Failure Control Module are suitable for a wide variety of single gen-set applications.

Monitoring engine speed, oil pressure, coolant temperature, frequency, voltage, current, power and fuel level, the modules give comprehensive engine and alternator protection. This is indicated on a large back-lit LCD text display via an array of warning, electrical trip and shutdown alarms in multiple languages.

Electronic J1939 (CAN) and non-electronic MPU and alternator sensing engine support for diesel, gas and petrol engines all in one variant. With a number of flexible inputs, outputs and protections, the modules can be easily adapted to suit a wide range of applications.

Through USB Communication both modules can be configured using the DSE Configuration Suite PC Software or through the module's front panel editor.

Using the DSE Configuration Suite PC Software the controller is easy to use and configure which allows alteration of operating parameters, sequences, timers and alarms.

### AVAILABLE VARIANTS

- 6110-03 Auto Start with real time clock
- 6120-03 Auto Mains Failure with real time clock

### ENVIRONMENTAL TESTING STANDARDS

**ELECTRO-MAGNETIC COMPATIBILITY**  
 BS EN 61000-6-2  
 EMC Generic Immunity Standard for the Industrial Environment  
 BS EN 61000-6-4  
 EMC Generic Emission Standard for the Industrial Environment

**ELECTRICAL SAFETY**  
 BS EN 60950  
 Safety of Information Technology Equipment, including Electrical Business Equipment

**TEMPERATURE**  
 BS EN 60068-2-1  
 Ab/Ae Cold Test -30 °C  
 BS EN 60068-2-2  
 Bb/Be Dry Heat +70 °C

**VIBRATION**  
 BS EN 60068-2-6  
 Ten sweeps in each of three major axes  
 5 Hz to 8 Hz at +/-7.5 mm,  
 8 Hz to 500 Hz at 2 GN

**HUMIDITY**  
 BS EN 60068-2-30  
 Db Damp Heat Cyclic 20/55 °C at 95% RH 48 Hours  
 BS EN 60068-2-78  
 Cab Damp Heat Static 40 °C at 93% RH 48 Hours

**SHOCK**  
 BS EN 60068-2-27  
 Three shocks in each of three major axes  
 15 GN in 11 mS

**DEGREES OF PROTECTION PROVIDED BY ENCLOSURES**  
 BS EN 60529  
 IP65 - Front of module when installed into the control panel with the optional sealing gasket.

## COMPREHENSIVE FEATURE LIST TO SUIT A WIDE VARIETY OF GEN-SET APPLICATIONS

